



SENSOR SWITCH


Item #	RBS05 Series	Description	TILT SWITCH	Version	V99.0
Page	1 of 4		Date	April 6, 2010	

● FUNCTIONS

45° Tilt Detecting within a 360° radius

● APPLICATIONS

1. Home appliance tilt-off function
2. Automotive devices
3. Visual devices
4. Information devices
5. Communication devices



● FEATURES

1. No electricity consumption during detection status.
2. Gold-plated ball and terminals, low possibility of oxidization.
3. All plastic materials subject to industrial purpose, resist high temperature and meet fireproof function.
4. Simple ON and OFF signals, easy for design.
5. RoHS compliance, an ideal substitute for mercury switch.
6. A more economical tilt detection option than IC design solution.
7. All made in Taiwan and examined before shipment.

● PATENTS

TAIWAN Patent NO. 226086

No.278, TsuYu Rd., Sec.4, E. Dist.,
Taichung City 40147, Taiwan

<http://www.oncque.com>
<http://www.oncque.com.tw>

TEL: 886-4-2212-2715

FAX: 886-4-2212-2717

E-mail: oncque@oncque.com.tw



SENSOR SWITCH

Item #	RBS05 Series	Description	TILT SWITCH	Version	V99.0
Page	2 of 4		Date	April 6, 2010	

● DIMENSIONS / OPERATION / P.C.B. LAYOUT (Unit: mm, Tolerance: $\pm 0.25\text{mm}$)

RBS 05 01 00			
--------------	--	--	--

RBS 05 02 00			
--------------	--	--	--

● ELECTRICAL CHARACTERISTICS

1.	Contact Rating	10mA, 5VDC
2.	Contact Resistance	100Ω max.
3.	Differential Angle	Refer to the drawing
4.	Switching Type	Normal Open (NO)
5.	Insulation Resistance	1,000MΩ min. at 100VDC
6.	Dielectric Strength	500VDC min. for 1 minute
7.	Capacitance	5pF max.

No.278, TsuYu Rd., Sec.4, E. Dist.,
Taichung City 40147, Taiwan

<http://www.oncque.com>
<http://www.oncque.com.tw>

TEL: 886-4-2212-2715

FAX: 886-4-2212-2717

E-mail: oncque@oncque.com.tw



SENSOR SWITCH

Item #	RBS05 Series	Description	TILT SWITCH	Version	V99.0
Page	3 of 4		Date	April 6, 2010	

● MECHANICAL CHARACTERISTICS

1.	Temperature Range	Operating: -25°C to +85°C Storage: -40°C to +85°C
2.	Pull Force of Terminal	500 gf for 1 minute
3.	Operation Life	100,000 cycles
4.	Humidity	95% RH, 40°C for 96 hrs.
5.	Solder Ability	After flux 245±5°C for 5±0.5 seconds 95% coverage

● BILL OF MATERIAL

1.	Housing	ZINC Alloy, Tin Plated over Nickel
2.	Cover	Polyamide + Glass-Fiber
3.	Terminal	Copper Alloy, Gold Plated over Nickel
4.	Ball	Copper Alloy, Gold Plated over Nickel
5.	Steel Ball	Stainless Steel

● PACKAGE

	Part Number	Package	Quantity	Total	Size
1.	RBS050100 RBS050200	PE Bag	500 pcs	500 pcs	12.7 x 17.8 (cm)
		Inner Box	10 Bags	5,000 pcs	36 x 20 x 9 (cm)
		Carton	3 Boxes	15,000 pcs	36 x 28 x 23 (cm)

* Minimum Order Quantity: One Bag

● NOTE

1. Suggestion for Application : Application in occasions that require vibration functions, adding design of "ON DELAY" is recommended. For great vibration, optical type products are recommended.
2. Suggestion Contact Rating: 5mA
3. Switches will provide pulse at tilt angle but the signal will not be a continued state after tilt angle.
4. For the continued product improvement as one of the company policy, specifications may change or update without notice. The latest information can be obtained through our sales offices. Normally, all products are supplied under our standard conditions.

No.278, TsuYu Rd., Sec.4, E. Dist.,
Taichung City 40147, Taiwan

<http://www.oncque.com>
<http://www.oncque.com.tw>

TEL: 886-4-2212-2715

FAX: 886-4-2212-2717

E-mail: oncque@oncque.com.tw



SENSOR SWITCH

Item #	RBS05 Series	Description	TILT SWITCH	Version	V99.0
Page	4 of 4		Date	April 6, 2010	

● PRECAUTIONS FOR USE

1. If the products is intended to be used for other endurance equipments requiring higher safety and reliability such as life support system, space and aviations devices, disaster and safety system, it's necessary to make verification of conformity or contact us for the details before using.
2. Don't try to clean the switch with a solvent or similar substance after the soldering process.
3. The switch might be damaged if using the water-soluble flux.
4. Don't use the switch in the environment with high humidity or other bedewing possibility, as it may cause leaking among the terminals.
5. It might catch fire if the rating exceeds the specifications. Never use the switch beyond the rating.

No.278, TsuYu Rd., Sec.4, E. Dist.,
Taichung City 40147, Taiwan

<http://www.oncque.com>
<http://www.oncque.com.tw>

TEL: 886-4-2212-2715

FAX: 886-4-2212-2717

E-mail: oncque@oncque.com.tw